



BUREAU  
VERITAS

# Certificat de conformité

Demandeur:

**Huawei Technologies Co., Ltd.**

Administration Building, Headquarters of Huawei Technologies Co., Ltd.,  
Bantian, Longgang District, Shenzhen, 518129,  
**P.R. China**

Produit:

**SOLAR INVERTER**

Modèle:

**SUN2000-15KTL-M3, SUN2000-17KTL-M3, SUN2000-20KTL-M3,**  
**SUN2000-23KTL-M3, SUN2000-30KTL-M3, SUN2000-36KTL-M3,**  
**SUN2000-40KTL-M3**

## À utiliser conformément aux réglementations:

Dispositif de coupure automatique avec une surveillance du réseau triphasé, conformément à C10/11 – 01.09.2019, pour des systèmes photovoltaïques avec un couplage parallèle triphasé, via un convertisseur dans l'alimentation électrique publique. Le dispositif de coupure automatique fait partie intégrante de ce convertisseur. Il remplace l'appareil de déconnexion avec une fonction isolante, auquel le fournisseur du réseau de distribution peut accéder à tout moment.

## Réglementations et normes appliquées:

**EN 50549-1:2019-02**

Exigences relatives aux centrales électriques destinées à être raccordées en parallèle à des réseaux de distribution - Partie 1: Raccordement à un réseau de distribution BT - Centrales électriques jusqu'au Type B inclus

4.4 Plage de fonctionnement normale

4.5 Immunité aux perturbations

4.6 Réponse active à l'écart de fréquence

4.7 Réponse de puissance aux variations de tension et aux changements de tension

4.8 CEM et qualité de l'alimentation

4.9 Protection d'interface

4.10 Connexion et démarrage de la production d'énergie électrique

4.11 Arrêt et réduction de la puissance active au point de consigne

4.13 Exigences concernant la tolérance de panne unique du système de protection d'interface et du commutateur d'interface

**C10/11:2019-09**

Prescriptions techniques spécifiques de raccordement d'installations de production décentralisée fonctionnant en parallèle sur le réseau de distribution

Un échantillon représentatif des produits mentionnés ci-dessus correspond à la date de la délivrance de ce certificat en vigueur des exigences de sécurité technique et pour l'utilisation conformément à sa destination.

Numéro de rapport: **PVBE200511N092**

Programme de certification: **NSOP-0032-DEU-ZE-V01**

Numéro de certificat: **U20-0901**

Delivré le:

**2020-11-11**

Organisme de certification

Thomas Lammel



Organisme de certification Bureau Veritas Consumer Products Services Germany GmbH accrédité par DIN EN ISO/IEC 17065

Une représentation partielle du certificat nécessite l'autorisation écrite de Bureau Veritas Consumer Products Services Germany GmbH



## Annex to the EN 50549-1 / C10/11 certificate of compliance No. U20-0901

### Appendix

Extract from test report according to EN 50549-1 / C10/11

Nr. PVBE200511N092

#### Type Approval and declaration of compliance with the requirements of EN 50549-1 / C10/11.

<b>Manufacturer / applicant:</b>	Huawei Technologies Co., Ltd. Administration Building, Headquarters of Huawei Technologies Co., Ltd., Bantian, Longgang District, Shenzhen, 518129, P.R. China							
<b>Micro-generator Type</b>								
	Photovoltaic inverter							
	SUN2000-15KTL-M3	SUN2000-17KTL-M3	SUN2000-20KTL-M3	SUN2000-23KTL-M3				
<b>MPP DC voltage range [V]</b>	200-1000							
<b>Input DC voltage range [V]</b>	200-1100							
<b>Input DC current [A]</b>	Max. 26A*4							
<b>Output AC voltage [V]</b>	230/400 Vac, 3W+N+PE; 50Hz							
<b>Output AC current [A]</b>	21,7A	24,5A	28,9A	33,3A				
<b>Output power [kW]</b>	15,0	17,0	20,0	23,0				
<b>Output power [kVA]</b>	16,5	18,7	22,0	23,0				
	SUN2000-30KTL-M3	SUN2000-36KTL-M3	SUN2000-40KTL-M3					
<b>MPP DC voltage range [V]</b>	200-1000							
<b>Input DC voltage range [V]</b>	200-1100							
<b>Input DC current [A]</b>	Max. 26A*4							
<b>Output AC voltage [V]</b>	230/400 Vac, 3W+N+PE; 50Hz							
<b>Output AC current [A]</b>	43,3A	52,0A	57,8A					
<b>Output power [kW]</b>	30,0	36,0	40,0					
<b>Output power [kVA]</b>	30,0	40,0	44,0					
<b>Firmware version</b>	V100R001							
<b>Measurement period:</b>	2020-05-11 - 2020-09-10							
<b>Description of the structure of the power generation unit:</b>								
The power generation unit is equipped with a PV and line-side EMC filter. The power generation unit has no galvanic isolation between DC input and AC output. Output switch-off is performed with single-fault tolerance based on two series-connected relays in (each) line and neutral. This enables a safe disconnection of the power generation unit from the network in case of error.								



## Annex to the EN 50549-1 / C10/11 certificate of compliance No. U20-0901

### Appendix

Extract from test report according to EN 50549-1 / C10/11

Nr. PVBE200511N092

#### Setting of the interface protection:

Parameter	Max. disconnection time	Min. operate time	Trip value
Over voltage (stage 1) <sup>a</sup>	0,2s	--	230V +10% (253V)
Over voltage (stage 2)	0,2s	0,1s	230V +15% (264,5V)
Under voltage	0,2s	0,1s	230V -20% (184V)
Over frequency	0,2s	0,1s	50Hz +3% (51,5Hz)
Under frequency	0,2s	0,1s	50Hz -5% (47,5Hz)
Reconnection settings for voltage (normal operational startup)	0,85V <sub>n</sub> (195,5V) ≤ V ≤ 1,10V <sub>n</sub> (253V)		
Reconnection settings for frequency (normal operational startup)	49,9Hz ≤ f ≤ 50,1Hz		
Reconnection time (normal operational startup)	≥60s		
Active power gradient (normal operational startup)	20% P <sub>Emax</sub> / per minute		
Reconnection settings for voltage (automatic reconnection after tripping)	0,85V <sub>n</sub> (195,5V) ≤ V ≤ 1,10V <sub>n</sub> (253V)		
Reconnection settings for frequency (automatic reconnection after tripping)	49,9Hz ≤ f ≤ 50,1Hz		
Reconnection time (automatic reconnection after tripping)	≥60s		
Active power gradient after reconnection	10% P <sub>Emax</sub> / per minute		
Active power delivery at under frequency	electronic inverter, no active power reduction		
Power response to over frequency (frequency / droop s)	50,2Hz / 5%		
Permanent DC-injection	0,5% of rated inverter output current or 20mA		
Rate of change of frequency (ROCOF)	2Hz/s		
Loss of mains according EN 62116 (LoM)	2,0s		

#### Note:

<sup>a</sup> Over voltage – stage1: 10 min-mean-value corresponding to EN 50160.

Default interface setting according to C10/11:2019-09 are used.

The settings of the interface protection are password protected adjustable.

In case the above stated generators are used with an external protection device, the protection settings of the inverters are to be adjusted according to the manufacturer's declaration.

The above stated generators are tested according to the requirements in the EN 50549-1:2019 and C10/11:2019. Any modification that affects the stated tests must be named by the manufacturer/supplier of the product to ensure that the product meets all requirements of the EN 50549-1:2019 and C10/11:2019.